



FOR CUSTOMER USE IF REQUIRED



RELAY CONTACTS RATED 4 AMPS AT 250VAC OR 5 AMPS AT 28VDC OR 120VAC AND 0.5 AMP AT 125VDC RESISTIVE LOAD.

NT2-24D AUDIBLE DEVICE WIRING

DIAGRAM SHOWS NOVATONE HORN WITH P1 TERMINAL BLOCK ON P.C. BOARD ATTACHED TO HORN (REF. DWG. 57100-48) FOR EARLIER VERSIONS WITH PIGTAIL LEADS, CONNECT BLACK TO OV. RED TO +24 AND BLUE TO FLASHER TERMINAL (REF. DWG. 57100-44).



ALARM PLUG-IN CARD MODEL NO.	9* AR 7
SINGLE POINT = 91 TWIN POINT = 92	
SEQUENCE CODE	
VARIATION ————————————————————————————————————	
INPUT OPTIONS DWG. LIST, REFER TO —— 91900—1 & 92900—1	
OUTPUT OPTIONS DWG. LIST, REFER TO $-$ 91900-2 & 92900-2	

OPERATIONAL SEQUENCE "FRRS"						
INPUT STATUS	VISUAL	ALARM AUDIBLE	RETURN AUDIBLE			
ALARM OR TEST	FAST FLASH	ON	OFF			
ACKNOWLEDGE	FAST FLASH	OFF	OFF			
FLASH RESET	STEADY-ON	OFF	OFF			
RETURN TO NORMAL	SLOW FLASH	OFF	ON			
RETURN ACKNOWLEDGE	SLOW FLASH	OFF	OFF			
RESET	OFF	OFF	OFF			

NOTES:

- 1. IF A NEW ALARM OCCURS WHILE TESTING. POINT WILL INDICATE ALARM CONDITION (RE-ALARM) AFTER FLASH RESET PUSHBUTTON IS OPERATED.
- 2. POINT WILL INDICATE ALARM WHEN TEST PUSHBUTTON IS OPERATED IF THE VISUAL INDICATOR IS OFF OR STEADY-ON.
- 3. IF POINT REALARMS WHILE SLOW FLASHING (RETURNED TO NORMAL) POINTS REVERTS TO ALARM STATUS.
- 4. A SINGLE AUDIBLE DEVICE MAY BE USED BY CONNECTING TERMINALS 6 & 7 OF THE FLASHER POSITION TOGETHER.

REV	ECN NO.	BY	APPD	DATE	MATERIAL: -			JNLESS CIFIED	
00	6781-04	DMW	ARF	02/18/81	FINISH:				
01	6783-38	ww	RAS	10/02/81	USED ON/REF. DWG	DESCRIPTION		.X = .015 .XX = .010	
02	8700-42	AK	JWK	05/19/83	91AR*	DRAWING LIST			= .005
03	9090-13	TA	AHD	10/02/84	92AR*	DRAWING LIST		MILLIMI X.O =	ETERS = 1.0
04	9431-03	IR	PG	04/19/88				0.X = 0.XX =	= 0.4
05	7099-74	SK	PG	06/06/89				ANGLES	
06	11872	SK	MIX	6/15/01				SCALE	INCH
					90450-AR7-1-0		@ 1981	NTS	(MM)

PANALARM 1725 WESTERN DRIVE, WEST CHICAGO, IL., 60185, U.S.A. PHONE: 1-630-231-5900 FAX: 1-630-231-4502 PAWLARM DWN. BY DMW/SM APPD/DATE ARF 02/18/81 THIRD ANGLE PROJECTION

CUSTOMER WIRING DIAGRAM AND SEQUENCE 'FRRS' INFORMATION FOR SERIES 90

SHFFT 1 OF 1

DWG. NO.

90450-AR7-1

-B-